

PRODUCTS
 **Phase Rotation Tester with fused test leads**

- [Multimeters](#)
- [Voltage Testers](#)

KEW 8031F

- [Clamp Meters](#)
- [Loggers](#)
- [Insulation Testers](#)
- [Earth Testers](#)
- [LOOP/PFC/PSC Testers](#)
- [RCD Testers](#)
- [Multi Function Testers](#)
- [Combi Tester](#)
- [Portable Appliance Testers](#)
- [Power Meters](#)
- [Sensors, Multi-Trans, Clamp Adaptors](#)
- [Others](#)
- [Accessories](#)
- [Discontinued Products](#)

- KEW8031F is designed to check phase sequence. Lamps provided on the unit will also tell you if a phase is open.
- Can check a wide range of 3-phase power source from 110V to 600V. Sealed against dust, the unit ensures trouble-free performance.
- Small, Lightweight and portable. Designed for maximum ease of operation and ruggedness.
- No exposed metal parts, Safety features are incorporated including the instant push button switch operation.



Operational Voltage	110~600V AC
Fuse	0.5A/600V (F)
Time limit for continuous	>500V : within 5 minutes
Frequency Response	50Hz/60Hz
Applicable Standards	IEC 61010-1 CAT.III 600V Pollution Degree 2
Withstand Voltage	5550V AC for 1 minute
Dimensions	106(L) × 75(W) × 40(D)mm
Weight	350g approx.
Cord	1.5m (R:red S:white T:blue)
Accessories	Carrying Case, Instruction Manual

 Page Top